

SPECIFICATION FOR APPROVAL

Product Specification

ion
ic

(lacktriangle) Final Specification

Title	32.0" WUXGA TFT LCD

BUYER	General
MODEL	

SUPPLIER	LG.Display Co., Ltd.
*MODEL	LC320EUJ
SUFFIX	FFE2(RoHS Verified)

^{*}When you obtain standard approval, please use the above model name without suffix

APPROVED BY	SIGNATURE DATE
,	
Please return 1 copy for your	confirmation with

your signature and comments.

APPROVED BY	SIGNATURE DATE				
J.T. Kim/ Team Leader					
REVIEWED BY					
S. J. Lee / Project Leader					
PREPARED BY					
J.K.Ahn / Engineer					
TV Products Development Dept. LG. Display LCD Co., Ltd					

Ver. 1.0 1/37

CONTENTS

Num	ber	ITEM	Page
		COVER	1
		CONTENTS	2
		RECORD OF REVISIONS	3
1		GENERAL DESCRIPTION	4
2		ABSOLUTE MAXIMUM RATINGS	5
3		ELECTRICAL SPECIFICATIONS	6
	3-1	ELECTRICAL CHARACTERISTICS	6
	3-2	INTERFACE CONNECTIONS	7
	3-3	SIGNAL TIMING SPECIFICATIONS	8
	3-4	LVDS SIGNAL SPECIFICATIONS	10
	3-5	INTARA INTERFACE SIGNAL SPECIFICATION	13
	3-6	COLOR DATA REFERENCE	14
	3-7	POWER SEQUENCE	15
4		OPTICAL SPECIFICATIONS	16
5		MECHANICAL CHARACTERISTICS	20
	5-1	BOARD ASSEMBLY DIMENSION	21
	5-2	CONTROL BOARD ASSEMBLY DIMMENSION	22
6		RELIABILITY	23
7		INTERNATIONAL STANDARDS	24
	7-1	ENVIRONMENT	24
8		PACKING	25
	8-1	PACKING FORM	25
9		PRECAUTIONS	26
	9-1	ASSEMBLY PRECAUTIONS	26
	9-2	OPERATING PRECAUTIONS	26
	9-3	ELECTROSTATIC DISCHARGE CONTROL	27
	9-4	PRECAUTIONS FOR STRONG LIGHT EXPOSURE	27
	9-5	STORAGE	27

Ver. 1.0 2 /37

RECORD OF REVISIONS


Revision No.	Revision Date	Page	Description
1.0	Feb, 13, 2013	-	Final Specification (First Draft)

Ver. 1.0 3 /37

1. General Description

The LC320EUJ is a Color Active Matrix Liquid Crystal Display with an integral the Source PCB and Gate implanted on Panel (GIP). The matrix employs a-Si Thin Film Transistor as the active element. It is a transmissive type display operating in the normally black mode. It has a 31.55 inch diagonally measured active display area with WUXGA resolution (1080 vertical by 1920 horizontal pixel array). Each pixel is divided into Red, Green and Blue sub-pixels or dots which are arranged in vertical stripes. Gray scale or the luminance of the sub-pixel color is determined with a 8-bit gray scale signal for each dot. Therefore, it can present a palette of more than 16.7Milion colors.

It is intended to support LCD TV, PCTV where high brightness, super wide viewing angle, high color gamut, high color depth and fast response time are important.



General Features

<u>Octional Foliatos</u>				
Active Screen Size	31.55 inch (801.31mm) diagonal			
Outline Dimension	714.0(H) x 411.0 (V) x 1.40 mm(D) (Typ.)			
Pixel Pitch	0.36375 mm x 0.36375 mm			
Pixel Format	1920 horiz. by 1080 vert. Pixels, RGB stripe arrangement			
Color Depth	8-bit, 16.7 M colors			
Luminance,White	2000cd/m²			
Power Consumption	Total 120W (Typ)			
Viewing Angle (CR>10)	Viewing angle free (R/L 178 (Min.), U/D 178 (Min.))			
Weight	5.0kg(Typ), 5.1kg(Max)			
Display Mode	Transmissive mode, Normally black			
Surface Treatment (Top)	Hard coating(3H), Anti-glare treatment of the front polarizer (Haze 1%(Typ.))			

Ver. 1.0 4 /37

2. Absolute Maximum Ratings


The following items are maximum values which, if exceeded, may cause faulty operation or permanent damage to the LCD module.

Table 1. ABSOLUTE MAXIMUM RATINGS

Parameter		Symbol	Va	Value		Note
		Symbol	Min	Max	Unit	Note
Power Input Voltage	LCD Circuit	VLCD	-0.3	+14.0	VDC	1
T-Con Option Selection Voltage		VLOGIC	-0.3	+4.0	VDC	
Operating Temperature		Тор	0	+50	°C	2.2
Storage Temperature		Тѕт	-20	+60	°C	2,3
Panel Front Temperature		Tsur	-	+68	°C	4
Operating Ambient Humidity		Нор	10	90	%RH	0.0
Storage Humidity		Нѕт	10	90	%RH	2,3

Note 1. Ambient temperature condition (Ta = 25 ± 2 °C)

- 2. Temperature and relative humidity range are shown in the figure below. Wet bulb temperature should be Max 39°C, and no condensation of water.
- 3. Gravity mura can be guaranteed below 40°C condition.
- 4. The maximum operating temperatures is based on the test condition that the surface temperature of display area is less than or equal to 68°C with LCD module alone in a temperature controlled chamber. Thermal management should be considered in final product design to prevent the surface temperature of display area from being over 68°C. The range of operating temperature may be degraded in case of improper thermal management in final product design.



Ver. 1.0 5 /37

3. Electrical Specifications


3-1. Electrical Characteristics

Table 2. ELECTRICAL CHARACTERISTICS

Parameter		Symbol	Value			Unit	Note
Falai	rarameter		Min	Тур	Max	Onit	Note
Circuit :							
Power Input Voltage		VLCD	10.8	12.0	13.2	VDC	
Power Input Current	Power Input Current		-	500	650	mA	1
Tower input ourient		ILCD	-	700	910	mA	2
T-CON Option	Input High Voltage	V _{IH}	2.7	-	3.6	VDC	
Selection Voltage	Input Low Voltage	V _{IL}	0	-	0.7	VDC	
Power Consumption		PLCD	-	150	153	Watt	1
Rush current		IRUSH	-	-	5.0	А	3

- 1. The specified current and power consumption are under the V_{LCD} =12.0V, Ta=25 \pm 2°C, f_V=60Hz condition, and mosaic pattern(8 x 6) is displayed and f_V is the frame frequency.
- 2. The current is specified at the maximum current pattern.
- 3. The duration of rush current is about 2ms and rising time of power input is 0.5ms (min.).
- 4. Ripple voltage level is recommended under $\pm 5\%$ of typical voltage

White: 255Gray Black: 0Gray



Mosaic Pattern(8 x 6)

Ver. 1.0 6/37

3-2. Interface Connections

3-2-1. LCD Module

- LCD Connector(CN1): FI-RE51S-HF(manufactured by JAE) or GT05P-51S-H38(manufactured by LSM) or IS050-C51B-C39(manufactured by UJU)

- Mating Connector: FI-R51HL(JAE) or compatible

Table 4-1. MODULE CONNECTOR(CN1) PIN CONFIGURATION

No	Symbol	Description	No	Symbol	Description
1	NC	No Connection (Note 4)	27	NC	No connection
2	NC	No Connection (Note 4)	28	R2AN	SECOND LVDS Receiver Signal (A-)
3	NC	No Connection (Note 4)	29	R2AP	SECOND LVDS Receiver Signal (A+)
4	NC	No Connection (Note 4)	30	R2BN	SECOND LVDS Receiver Signal (B-)
5	NC	No Connection (Note 4)	31	R2BP	SECOND LVDS Receiver Signal (B+)
6	NC	No Connection (Note 4)	32	R2CN	SECOND LVDS Receiver Signal (C-)
7	LVDS Select	'H' =JEIDA , 'L' or NC = VESA	33	R2CP	SECOND LVDS Receiver Signal (C+)
8	NC	No Connection (Note 4)	34	GND	Ground
9	NC	No Connection (Note 4)	35	R2CLKN	SECOND LVDS Receiver Clock Signal(-)
10	NC	No Connection (Note 4)	36	R2CLKP	SECOND LVDS Receiver Clock Signal(+)
11	GND	Ground	37	GND	Ground
12	R1AN	FIRST LVDS Receiver Signal (A-)	38	R2DN	SECOND LVDS Receiver Signal (D-)
13	R1AP	FIRST LVDS Receiver Signal (A+)	39	R2DP	SECOND LVDS Receiver Signal (D+)
14	R1BN	FIRST LVDS Receiver Signal (B-)	40	NC	No connection
15	R1BP	FIRST LVDS Receiver Signal (B+)	41	NC	No connection
16	R1CN	FIRST LVDS Receiver Signal (C-)	42	NC or GND	No Connection or Ground
17	R1CP	FIRST LVDS Receiver Signal (C+)	43	NC or GND	No Connection or Ground
18	GND	Ground	44	GND	Ground (Note 5)
19	R1CLKN	FIRST LVDS Receiver Clock Signal(-)	45	GND	Ground
20	R1CLKP	FIRST LVDS Receiver Clock Signal(+)	46	GND	Ground
21	GND	Ground	47	NC	No connection
22	R1DN	FIRST LVDS Receiver Signal (D-)	48	VLCD	Power Supply +12.0V
23	R1DP	FIRST LVDS Receiver Signal (D+)	49	VLCD	Power Supply +12.0V
24	NC	No connection	50	VLCD	Power Supply +12.0V
25	NC	No connection	51	VLCD	Power Supply +12.0V
26	NC or GND	No Connection or Ground	-	-	-

Note

- 1. All GND(ground) pins should be connected together to the LCD module's metal frame.
- 2. All VLCD (power input) pins should be connected together.
- 3. All Input levels of LVDS signals are based on the EIA 644 Standard.
- 4. #1~#6 & #8~#10 NC (No Connection): These pins are used only for LGD (Do not connect)
- 5. Specific pin No. **#44** is used for "No signal detection" of system signal interface. It should be GND for NSB(No Signal Black) during the system interface signal is not. If this pin is "H", LCD Module displays AGP(Auto Generation Pattern).

Ver. 1.0 7 /37

3-3. Signal Timing Specifications

Table 6 shows the signal timing required at the input of the LVDS transmitter. All of the interface signal timings should be satisfied with the following specification for normal operation.

Table 6. TIMING TABLE (DE Only Mode)


ITE	ITEM		Min Typ		Max	Unit	notes
	Display Period	tHV	960	960	960	tCLK	1920 / 2
Horizontal	Blank	tнв	100	140	240	tCLK	1
	Total	tHP	1060	1100	1200	tCLK	
	Display Period	tvv	1080	1080	1080	Lines	
Vertical	Blank	t∨B	20 (228)	45 (270)	69 (300)	Lines	1
	Total	tvp	1100 (1308)	1125 (1350)	1149 (1380)	Lines	

ITE	М	Symbol	Min	Тур	Max	Unit	notes
	DCLK	fclk	63.00	74.25	78.00	MHz	
	Horizontal	fн	57.3	67.5	70	KHz	2
Frequency	Vertical	fv	57 (47)	60 (50)	63 (53)	Hz	2 NTSC (PAL)

- notes: 1. The input of HSYNC & VSYNC signal does not have an effect on normal operation (DE Only Mode). If you use spread spectrum of EMI, add some additional clock to minimum value for clock margin.
 - 2. The performance of the electro-optical characteristics may be influenced by variance of the vertical refresh rate and the horizontal frequency
 - 3. Spread Spectrum Rate (SSR) for 50KHz ~ 100kHz Modulation Frequency(FMOD) is calculated by (7 0.06*Fmod), where Modulation Frequency (FMOD) unit is KHz. LVDS Receiver Spread spectrum Clock is defined as below figure

* Timing should be set based on clock frequency.

Ver. 1.0 8 /37




- ** Please pay attention to the followings when you set Spread Spectrum Rate(SSR) and Modulation Frequency(FMOD)
- 1. Please set proper Spread Spectrum Rate(SSR) and Modulation Frequency (FMOD) of TV system LVDS output.
- 2. Please check FOS after you set Spread Spectrum Rate(SSR) and Modulation Frequency(FMOD) to avoid abnormal display. Especially, harmonic noise can appear when you use Spread Spectrum under FMOD 30 KHz.

Ver. 1.0 9 /37

3-4. LVDS Signal Specification


3-4-1. LVDS Input Signal Timing Diagram



Ver. 1.0 10 /37


3-4-2. LVDS Input Signal Characteristics

1) DC Specification



Description	Symbol	Min	Max	Unit	Note
LVDS Common mode Voltage	V _{CM}	1.0	1.5	V	-
LVDS Input Voltage Range	V _{IN}	0.7	1.8	V	
Change in common mode Voltage	ΔVCM	-	250	mV	-


2) AC Specification



Description	Symbol	Min	Max	Unit	Note	
LVDS Differential Voltage	High Threshold	V_{TH}	100	300	mV	2
LVDS Differential Voltage	Low Threshold	V_{TL}	-300	-100	mV	J
LVDS Clock to Data Skew	t _{SKEW}	-	(0.20*T _{clk})/7	ps	-	
LVDS Clock/DATA Rising/Falli	t _{RF}	260	(0.3*T _{clk})/7	ps	2	
Effective time of LVDS	t _{eff}	±360	-	ps	-	
LVDS Clock to Clock Skew (E	ven to Odd)	t _{SKEW_EO}	-	1/7* T _{clk}	ps	-

Note 1. All Input levels of LVDS signals are based on the EIA 644 Standard.

- 2. If t_{RF} isn't enough, t_{eff} should be meet the range.
- 3. LVDS Differential Voltage is defined within teff




^{*} This accumulated waveform is tested with differential probe


3-5. Intra interface Signal Specification

3-5-1. EPI Signal Specification


Table 5. ELECTRICAL CHARACTERISTICS

Parameter	Symbol	Condition	MIN	TYP	MAX	Unit	notes
Logic & EPI Power Voltage	VCC	-	1.62	1.8	1.98	VDC	
EPI input common voltage	VCM	LVDS Type	0.8	VCC/2	1.3	V	
EPI input differential voltage	Vdiff	-	150	-	500	mV	
EPI Input eye diagram	Veye	-	90	-	-	mV	





EPI Differential signal characteristics



Eye Pattern of EPI Input



FIG. 3 Measure point

3-6. Color Data Reference

The brightness of each primary color(red,green,blue) is based on the 8bit gray scale data input for the color. The higher binary input, the brighter the color. Table 6 provides a reference for color versus data input.

Table 6. COLOR DATA REFERENCE

											I	npu	t Co	lor [Data										
	Color				RE	D							GRI	EEN	l						BL	UE			
	COIOI	MS	B 					LS	SB	MS	SB ——					L:	SB	MS	SB ——					L	SB
		R	7 R6	R5	R4	R3	R2 F	₹1 R	0	G	7 G6	G5	G4	G3	G2 (G1 (30	В	7 B	6 B5	B4	В3	B2 I	31 E	30
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (255)	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green (255)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
Basic	Blue (255)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
Color	Cyan	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	RED (000)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (001)	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
RED																									
	RED (254)	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (255)	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (000)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (001)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0
GREEN																									
	GREEN (254)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0
	GREEN (255)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	BLUE (000)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	BLUE (001)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
BLUE																									
	BLUE (254)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0
	BLUE (255)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1

3-7. Power Sequence

3-6-1. LCD Driving circuit




Table 8. POWER SEQUENCE

Dovementor		Value		11-14	Netes	
Parameter	Min	Тур	Max	Unit	Notes	
T1	0.5	-	20	ms	1	
T2	0	-	-	ms	2	
Т3	400	-	-	ms	3	
T4	200	-	-	ms	3	
T5	1.0	-	-	s	4	
T6	0	-	T2	ms	5	
T7	0	-	-	ms	6	

Note:

- 1. Even though T1 is over the specified value, there is no problem if I2T spec of fuse is satisfied.
- 2. If T2 is satisfied with specification after removing LVDS Cable, there is no problem.
- 3. The T3 / T4 is recommended value, the case when failed to meet a minimum specification, abnormal display would be shown. There is no reliability problem.
- 4. T5 should be measured after the Module has been fully discharged between power off and on period.
- 5. If the on time of signals (Interface signal and user control signals) precedes the on time of Power (V_{LCD}), it will be happened abnormal display. When T6 is NC status, T6 doesn't need to be measured.
- 6. It is recommendation specification that T7 has to be 0ms as a minimum value.
- Please avoid floating state of interface signal at invalid period.
- * When the power supply for LCD (VLCD) is off, be sure to pull down the valid and invalid data to 0V.

Ver. 1.0 15 /37

4. Optical Specification

Optical characteristics are determined after the unit has been 'ON' and stable in a dark environment at $25\pm2^{\circ}$ C. The values are specified at 50cm from the LCD surface at a viewing angle of Φ and θ equal to 0 °. FIG. 1 shows additional information concerning the measurement equipment and method.




FIG. 1 Optical Characteristic Measurement Equipment and Method

Ta= $25\pm2^{\circ}$ C, V_{LCD}=12.0V, fv=60Hz, Dclk=74.25MHz,

Table 10. OPTICAL CHARACTERISTICS

EXTVBR-B =100% Back Light : LGD B/L

Down		Comple ed		Value		l lmit	Note		
Para	ameter	Symbol	Min	Тур	Max	Unit	NOTE		
Contrast Ratio		CR	1000	1400	-		1		
Daananaa Tima	Variation	G to G $_{\sigma}$		6	9		5		
Response Time	Gray to Gray (BW)	G to G BW		8	12	ms	4		
	DED	Rx		0.638					
	RED	Ry	ĺ	0.334	Typ +0.03				
Color Coordinates	ODEEN	Gx	ј Тур	0.312					
[CIE1931]	GREEN	Gy	-0.03	0.595					
	BLUE	Bx		0.154					
		Ву		0.061					
Viewing Angle (CF	R>10)			ĺ					
x axi	s, right(φ=0°)	θr	89	-	-				
x axi	s, left (φ=180°)	θΙ	89	-	-				
	s, up (φ=90°)	θu	89	-	-	degree	6		
l .	s, down (φ=270°)	θd	89	-	-				
Gray Scale			-	-	-		7		

Ver. 1.0 16/37

Note: 1. Contrast Ratio(CR) is defined mathematically as:

CR(Contrast Ratio) = Center 1 Point at n=1(See FIG 2.)

Surface Luminance at position n=1 with all white pixels

CRn =

Surface Luminance at position n=1 with all black pixels

n = 1 is the Position of CR Measurement. For more information, see FIG 2.

- 2. Surface luminance are determined after the unit has been 'ON' and 1 Hour after lighting the backlight in a dark environment at 25±2°C. Surface luminance is the luminance value at center 1-point across the LCD surface 50cm from the surface with all pixels displaying white. For more information see the FIG. 2.
- 4. Response time is the time required for the display to transit from any gray to white (Rise Time, Tr_R) and from any gray to black (Decay time, Tr_D). For additional information see the FIG. 3.

※ G to G_{BW} Spec stands for average value of all measured points.

Photo Detector: RD-80S / Field: 2°

5. G to G $_{\sigma}$ is Variation of Gray to Gray response time composing a picture

G to G (σ) = $\sqrt{\frac{\sum (Xi-u)^2}{N}}$ Xi = Individual Data u = Data averageN : The number of Data

- 6. Viewing angle is the angle at which the contrast ratio is greater than 10. The angles are determined for the horizontal or x axis and the vertical or y axis with respect to the z axis which is normal to the LCD module surface. For more information, see the FIG. 4.
- 7. Gray scale specification
 Gamma Value is approximately 2.2. For more information, see the Table 11.

Table 11. GRAY SCALE SPECIFICATION

Gray Level	Luminance [%] (Typ.)
LO	0.07
L15	0.27
L31	1.04
L47	2.49
L63	4.68
L79	7.66
L95	11.5
L111	16.1
L127	21.6
L143	28.1
L159	35.4
L175	43.7
L191	53.0
L207	63.2
L223	74.5
L239	86.7
L255	100

Ver. 1.0 17 /37

Measuring point for surface luminance.




FIG. 2 5 Points for Luminance Measure

Response time is defined as the following figure and shall be measured by switching the input signal for "Gray(N)" and "Black or White".




FIG. 3 Response Time

Ver. 1.0 18 /37

Dimension of viewing angle range




FIG. 4 Viewing Angle

Ver. 1.0 19 /37

5. Mechanical Characteristics


Table 9 provides general mechanical characteristics.

Table 9. MECHANICAL CHARACTERISTICS

Item	Value	Value				
	Horizontal	714.0mm				
Outline Dimension (Only Glass)	Vertical	411.0mm				
(O.i.) Class,	Thickness	1.40 mm				
A .: - B: - L . A	Horizontal	698.4 mm				
Active Display Area	Vertical	392.85 mm				
Weight	840g(Typ), 880g(Max)					
Surface Treatment	Hard coating(3H), Anti-glare treatment of the front polarizer : Haze 1%(typ.)					

notes: Please refer to a mechanic drawing in terms of tolerance at the next page.

Ver. 1.0 20 /37



6. Reliability

Table 13. ENVIRONMENT TEST CONDITION

No.	Test Item	Condition			
1	High temperature storage test	Ta= 60°C 240h			
2	Low temperature storage test	Ta= -20°C 240h			
3	High temperature operation test	Ta= 50°C 50%RH 240h			
4	Low temperature operation test	Ta= 0°C 240h			
7	Humidity condition Operation	Ta= 40 °C ,90%RH			
8	Altitude operating storage / shipment	0 - 16,400 ft 0 - 40,000 ft			

Note: Before and after Reliability test, LCM should be operated with normal function.

Ver. 1.0 23 /37

7. International Standards

7-1. Environment

a) RoHS, Directive 2002/95/EC of the European Parliament and of the council of 27 January 2003

Ver. 1.0 24 /37

8. Packing

8-1. Packing Form

a) Package quantity in one Pallet: 160 pcs

b) Pallet Size :1140 mm(L) X 910 mm(W) X 1085 mm(H)

Ver. 1.0 25 /37

9. Precautions

Please pay attention to the followings when you use this TFT LCD module.

9-1. Assembly Precautions

- (1) Please attach the surface transparent protective plate to the surface in order to protect the polarizer. Transparent protective plate should have sufficient strength in order to the resist external force.
- (2) You should adopt radiation structure to satisfy the temperature specification.
- (3) Acetic acid type and chlorine type materials for the cover case are not desirable because the former generates corrosive gas of attacking the polarizer at high temperature and the latter causes circuit break by electro-chemical reaction.
- (4) Do not touch, push or rub the exposed polarizers with glass, tweezers or anything harder than HB pencil lead. And please do not rub with dust clothes with chemical treatment.
 Do not touch the surface of polarizer for bare hand or greasy cloth. (Some cosmetics are detrimental to the polarizer.)
- (5) When the surface becomes dusty, please wipe gently with absorbent cotton or other soft materials like chamois soaks with petroleum benzine. Normal-hexane is recommended for cleaning the adhesives used to attach front / rear polarizers. Do not use acetone, toluene and alcohol because they cause chemical damage to the polarizer
- (6) Wipe off saliva or water drops as soon as possible. Their long time contact with polarizer causes deformations and color fading.
- (7) Board ass'y should be put on the mold frame properly.
- (8) FFC Cable should be connected between System board and Source PCB correctly.
- (9) Mechanical structure for backlight system should be designed for sustaining board ass'y safely.

9-2. Operating Precautions

- (1) Response time depends on the temperature.(In lower temperature, it becomes longer.)
- (2) Brightness depends on the temperature. (In lower temperature, it becomes lower.)

 And in lower temperature, response time(required time that brightness is stable after turned on) becomes longer
- (3) Be careful for condensation at sudden temperature change. Condensation makes damage to polarizer or electrical contacted parts. And after fading condensation, smear or spot will occur.
- (4) When fixed patterns are displayed for a long time, remnant image is likely to occur.
- (5) Module has high frequency circuits. Sufficient suppression to the electromagnetic interference shall be done by system manufacturers. Grounding and shielding methods may be important to minimized the interference.
- (6) Please do not give any mechanical and/or acoustical impact to LCM. Otherwise, LCM can't be operated its full characteristics perfectly.

Ver. 1.0 26 /37

9-3. Electrostatic Discharge Control

Since a module is composed of electronic circuits, it is not strong to electrostatic discharge. Make certain that treatment persons are connected to ground through wrist band etc. And don't touch interface pin directly. Panel ground path should be connected to metal ground.

9-4. Precautions for Strong Light Exposure

Strong light exposure causes degradation of polarizer and color filter.

9-5. Storage

When storing modules as spares for a long time, the following precautions are necessary.

- (1) Store them in a dark place. Do not expose the module to sunlight or fluorescent light. Keep the temperature between 5°C and 35°C at normal humidity.
- (2) The polarizer surface should not come in contact with any other object.


 It is recommended that they be stored in the container in which they were shipped.


Ver. 1.0 27 /37

APPENDIX-I


■ Pallet Ass'y















⑤





No.	Description	Material			
(a)	Pallet	Plywood			
b	Carton Plate	Single Wall			
©	PE Sheet	Carbon			
(d)	Top Packing	EPS			
Θ	Bottom Packing	EPS			
(f)	Angle Packing	Single Wall			
9	Tape	OPP			
h	Band	PP			
(i)	Clip	PP			


APPENDIX- | -2

■ Control PCB Packing Ass'y

a) Control PCB Qty / Box : 160 pcs

b) Tray Qty / Box : 17Tray(Upperst Tray Is empty)

c) Tray Size : 466 X 353 X 16 d) Box size : 468 X 355 X 197



NO.	DESCRIPTION	MATERIAL	
1	PCB Packing A,ssy	-	
2	Tray	PET	
3	Box	SWR4	

Ver. 1.0 29 /37

APPENDIX- II-1


■ Board Ass'y ID Label



Ver. 1.0 30 /37

APPENDIX- II-2

■ Box Label




■ Pallet Label



Ver. 1.0 31 /37

APPENDIX- III-1

■ Required signal assignment for Flat Link (Thine: THC63LVD103) Transmitter(Pin7= "L" or "NC")




Note: 1. The LCD module uses a 100 $Ohm[\Omega]$ resistor between positive and negative lines of each receiver input.

- 2. Refer to LVDS Transmitter Data Sheet for detail descriptions. (THC63LVD103 or Compatible)
- 3. '7' means MSB and '0' means LSB at R,G,B pixel data.

APPENDIX- III-2

■ Required signal assignment for Flat Link (Thine: THC63LVD103) Transmitter(Pin7= "H")



Note :1. The LCD module uses a 100 $Ohm[\Omega]$ resistor between positive and negative lines of each receiver input.


- 2. Refer to LVDS Transmitter Data Sheet for detail descriptions. (THC63LVD103 or Compatible)
- 3. '7' means MSB and '0' means LSB at R,G,B pixel data.

33 /37


APPENDIX- IV

■ LVDS Data-Mapping Information (8 Bit)

1) LVDS Select: "H" Data-Mapping (JEIDA format)



2) LVDS Select: "L" Data-Mapping (VESA format)




Ver. 1.0 34/37

APPENDIX- V

■ Option Pin Circuit Block Diagram

Circuit Block Diagram of LVDS Format Selection pin





Ver. 1.0 35 /37

APPENDIX-VI

. Flicker Adjustment

Parameter	Unit	Min	Тур	Max	Note
Inversion Method	- V-2Dot Inversion		1		
Adjust Pattern / Gray Level	-	G2Dot Full Flicker / 223Gray		60Hz	
Position	-	Center			
Voltage range V		6.5	6.8	7.1	








FIG. 8 VCOM Adjustment Pattern & Block Diagram

Ver. 1.0 36 /37


APPENDIX-VII


■ The reference method of BL burst dimming

It is recommended to use synchronous V-sync frequency to prevent waterfall (Vsync * 2 =Burst Frequency)

Ver. 1.0 37 /37

APPENDIX-IX





Note

- Pad: GOLD Plating

- # ≥ Cpk 1.0

- ## ≥ Cpk 1.33

- Stiffener color : Sky Blue

- H-F

- Dimensions unit: mm

- Material List

APPLICATION	STANDARD	MATERIAL	REFERENCE
1. CONDUCTOR	GOLD PLATED COPPER WIRE	1. 99.99% COPPER	Tolerance THICKNESS: ±0.01
		2. GOLD PLATED	- WIDTH: +0.04 -0.02
		2. GOLD PLATED	Service of the servic
			2. ELOGATION(%):
			10 MORE THAN
			3. TENSION:
			(KGF) 0.2 MORE THAN
			4. GOLD THICKNESS: 0.05 µm MIN
			*MAKER: TAIHAN ELECTRIC
			plating process : J MICRON/SUNEUN
2. INSULATION	POLYESTER FILM (PET/PET)	1. POLYESTER	UL VW-1 FLAME
	(FEI/FEI)	BASE FILM: 0.025 mm	Width: 120mm
		2. POLYESTER HOTMELT	Length: 500M
			UNIT: ROLL
		ADHESIVE : 0.035 mm	
		TOTAL : 0.060 mm	* MAKER : SHINCHANG HOTMELT/ COSMOAMT
3. SUPPORTING TAPE	POLYESTER FILM	1. POLYESTER	Width : 20.5mm
		BASE FILM: 0.188 mm	
		2. POLYESTER HOTMELT	Length : 250M Unit : ROLL
		ADHESIVE : 0.027 mm	*MAKER :
		TOTAL THICKNESS : 0.215 mm	SUNGSHIN Trading/ COSMOAMT
4. SILICON TAPE		TOTAL THICKNESS: 0.065 mm	1
(BROWN)			*MAKER : DAEHYUN ST

Ver. 1.0 38 /37